

# 高周波フィルタ Coaxial Filters

代表形状  
Representatives



区分/品名 Type /Product #		周波数範囲 Frequency range (MHz)	挿入損失 Insertion loss(dB)	減衰量 Attenuation (dB)	V.S.W.R.	
Low Pass Filter	LPF060M-K09N238	40~90MHz z の指定通過周波数FP Assigned Freq. in 40~90MHz	<1.0	FP×2、FP×3 >40	<1.3	
	LPF150M-K09N238	130~170MHz z の指定周波数FP Assigned Freq. in 130~170MHz				
	LPF260M-K09N239	200~280MHz z の指定周波数FP Assigned Freq. in 200~280MHz				
	LPF400M-K09N240	330~770MHz z の指定周波数FP Assigned Freq. in 330~770MHz				
High Pass Filter	HPF150M-K09N241	130~170MHz z の指定周波数FP Assigned Freq. in 130~170MHz	<1.0	1/2FP >40	<1.3	
	HPF260M-K09N242	200~280MHz z の指定周波数FP Assigned Freq. in 200~280MHz				
	HPF400M-K09N243	330~770MHz z の指定周波数FP Assigned Freq. in 330~770MHz				
Band Pass Filter	BPF060M-0070H02N227	50~70MHz z 帯の指定周波数Fo Assigned Freq. in 50~70MHz	<1.0	Fo±2.5MHz >20	<1.3	
	BPF060M-0100H03N228	50~70MHz z 帯の指定周波数Fo Assigned Freq. in 50~70MHz		Fo±1.5MHz >20		
	BPF060M-0100H04N332	70~90MHz z 帯の指定周波数Fo Assigned Freq. in 70~90MHz		Fo±1.0MHz >35		
	BPF150M-0100C03N214	130~170MHz z の指定周波数Fo Assigned Freq. in 130~170MHz		Fo±2.0MHz >30		
	BPF150M-0150CH03N272	130~170MHz z の指定周波数Fo Assigned Freq. in 130~170MHz		Fo±1.0MHz >20		
	BPF200M-0080C08N326	170~220MHz z の指定周波数Fo±5MHz z Assigned Freq. fo ± 5MHz in 170~220MHz		Fo±8.0MHz >35		
	BPF260M-0070C06N348	260~280MHz z の指定周波数Fo±1.5MHz z Assigned Freq. fo ± 1.5MHz in 260~280MHz		Fo±8.0MHz >80		
	BPF260M-0070C04N349	260~280MHz z の指定周波数Fo±1.5MHz z Assigned Freq. fo ± 1.5MHz in 260~280MHz		Fo±8.0MHz >60		
	BPF400M-0050C03N278	330~470MHz z の指定周波数Fo Assigned Freq. in 330~470MHz		Fo±8.0MHz >40		
	BPF400M-0033C05N346	470~770MHz z の指定周波数Fo±2.79MHz Assigned Freq. fo ± 2.79MHz in 470~770MHz		Fo±4.36MHz >15		
	BPF400M-0010H04N413	470~770MHz z の指定周波数Fo±3.0MHz Assigned Freq. fo ± 3.0MHz in 470~770MHz		Fo±30MHz >50		<1.7
	BPF800M-0080D06N363	800MHz z 帯の指定周波数Fo±4.0MHz z Assigned Freq. fo ± 4.0MHz in the range of 800MHz		Fo±37MHz >70		
	BPF1.2G-0100D16N403	1,200MHz z 帯の指定周波数Fo±8.5MHz z Assigned Freq. fo ± 8.5MHz in the range of 1,200MHz		Fo±10.5MHz >50		<1.3
BPF002G-0006D04N340	2,300MHz z 帯の指定周波数Fo±8.5MHz z Assigned Freq. fo ± 8.5MHz in the range of 2,300MHz					
Band Elimination Filter	BEF060M-0070H02N213	50~70MHz z 帯の指定周波数FP Assigned Freq. in 50~70MHz	<1.0	FP~1MHz>FE >50	<1.3	
	BEF060M-0043H03N215	50~70MHz z 帯の指定周波数FP Assigned Freq. in 50~70MHz		FP~1.5MHz>FE >50		
	BEF260M-0070C01N229	260~280MHz z の指定周波数FP Assigned Freq. in 260~280MHz		FP~0.7MHz>FE >15		
DUP	DUP260M-0070C12N251	260~280MHz z の指定周波数FT、及びFR(FT~FR>8MHz z) Assigned Freq. FT in 260~280MHz And FR(FT~FR>8MHz)	<1.0	>80	<1.3	
	DUP500M-0100C08N248	470~770MHz z の指定周波数F1±2.79MHz、及びF2±2.79MHz z Assigned Freq. F1±2.79MHz in 470~770MHz And F2±2.79MHz z		±4.36MHz >15		